


	DEIF Battery Charger, DBC-1 1205 	DEIF Battery Charger, DBC-1 1210 	
Main function:	The DBC-1 is a charger for lead acid and gel batteries.	The DBC-1 is a charger for lead acid and gel batteries.	
Input voltage:	1 × 115V AC/1 × 230V AC ±15% 47...63 Hz	1 × 115V AC/1 × 230V AC ±15% 47...63 Hz	
Output voltage:	13.8V DC (adjustable 12.6...15.1V DC)	27.6V DC (adjustable 25.2...30.2V DC)	
Output current:	5 A (maximum 6 A)	10 A (maximum 12 A)	
Protection:	IP 20	IP 20	
Size:	W: 150 mm (5.91") H: 116 mm (4.57") D: 79 mm (3.11")	W: 150 mm (5.91") H: 116 mm (4.57") D: 79 mm (3.11")	
Weight:	Approx. 0.68 kg (1.5 lbs)	Approx. 0.74 kg (1.6 lbs)	

	DEIF Battery Charger, DBC-1 2405 	DEIF Battery Charger, DBC-1 2410 	
Main function:	The DBC-1 is a charger for lead acid and gel batteries.	The DBC-1 is a charger for lead acid and gel batteries.	
Input voltage:	1 × 115V AC/1 × 230V AC ±15% 47...63 Hz	1 × 115V AC/1 × 230V AC ±15% 47...63 Hz	
Output voltage:	13.8V DC (adjustable 12.6...15.1V DC)	27.6V DC (adjustable 25.2...30.2V DC)	
Output current:	5 A (maximum 6 A)	10 A (maximum 12 A)	
Protection:	IP 20	IP 20	
Size:	W: 150 mm (5.91") H: 116 mm (4.57") D: 79 mm (3.11")	W: 189 mm (7.44") H: 120 mm (4.72") D: 79 mm (3.11")	
Weight:	Approx. 0.74 kg (1.6 lbs)	0.85 kg (1.87 lbs)	

	Battery Charger, DCP2-1205 	Battery Charger, DCP2-2405 	Battery Charger, DCP2-1210 
Main function:	The DCP2 can be applied as battery charger or as a universal DC voltage supply.	The DCP2 can be applied as battery charger or as a universal DC voltage supply.	The DCP2 can be applied as battery charger or as a universal DC voltage supply.
Input voltage:	1 × 230V AC ±15% 47...63 Hz	1 × 230V AC ±15% 47...63 Hz	1 × 230V AC ±15% 47...63 Hz
Output voltage:	12V DC (adjustable 11.8...13.8V DC)	24V DC (adjustable 23.5...27.5V DC)	12V DC (adjustable 11.8...13.8V DC)
Output current:	5 A (typical current limit 6 A)	5 A (typical current limit 6 A)	10 A (typical current limit 12.5 A)
Protection:	IP20	IP20	IP20
Size:	147 × 123 × 86 mm	147 × 123 × 86 mm	205 × 123 × 86 mm
Weight:	Approx. 0.8 kg	Approx. 0.8 kg	Approx. 1.2 kg
	Battery Charger, DCP2-2410 	Battery Charger, DCP2-2420 	Battery Charger, DCP2-2420 
Main function:	The DCP2 can be applied as battery charger or as a universal DC voltage supply.	The DCP2 can be applied as battery charger or as a universal DC voltage supply.	The DCP2 can be applied as battery charger or as a universal DC voltage supply.
Input voltage:	1 × 115V AC ±15% 1 × 230V AC ±15% 47...63 Hz	1 × 230V AC ±15% 47...63 Hz	3 × 400/480V AC ±15% 47...63 Hz
Output voltage:	24V DC (adjustable 23.5...27.5V DC)	24V DC (adjustable 23.5...27.5V DC)	24V DC (adjustable 23.5...27.5V DC)
Output current:	10 A (typical current limit 12.5 A)	20 A (typical current limit 25 A)	20 A (typical current limit 25 A)
Protection:	IP20	IP20	IP20
Size:	205 × 123 × 86 mm	240 × 153 × 86 mm	240 × 153 × 86 mm
Weight:	Approx. 1.2 kg	Approx. 1.9 kg	Approx. 1.9 kg

